

# Mi Motion-Activated Night Light 2 User Manual



**EN**

## Product Overview

Read this manual carefully before use, and retain it for future reference.

Front

Interior

Illustrations of product, accessories, and user interface in the user manual are for reference purposes only. Actual product and functions may vary due to product enhancements.

01

**EN**

## How to Use

### 1. Installing the batteries

Turn the front cover counterclockwise to unscrew it from its hemispherical housing. Open the battery cover and install three AA batteries in the battery compartment.

### 2. Toggle the brightness switch to the desired brightness level before screwing the lamp back into its hemispherical housing.

3 lm

25 lm

Places that are suitable for use as a night light: bathrooms, hallways, bedrooms, and children's rooms.

Places that are suitable for use as an auxiliary light: doorways, entrances, wardrobes, wall surfaces, and balconies.

02

**EN**

## 3. Mounting the light

Select a flat and dry mounting surface, wipe the surface clean first, and then peel off the release liner from the base. Stick the base in the desired location and press it down firmly to make sure it is properly secured. Finally, attach the light to the magnetic base and adjust it to a suitable angle. Make sure it is firmly installed with the magnet, so as to avoid the risk of accidental dropping.

Note: For accurate detection, it is recommended to face the light downwards when the base has been mounted over 1.9 m above the floor.

Mounting point is over 1.9 m above the floor

Facing downwards

Mounting point is between 0.5–1.5 m above the floor

Facing straight forward

03

**EN**

Mounting point is below 0.5 m above the floor

Facing upwards

Note: For different mounting heights, the angle needs to be adjusted based on the user's height and the desired usage scenario to achieve the optimal result.

### 4. When it is dark and body movement is detected, the light will turn on automatically, and turn off automatically after 15 seconds if no further body movement is detected.

Detection Area

Note: The detection area is a 120° area directly at the center in front of the night light. The detection area covers 0–6 m in front of the light, and 0–2.5 m to the sides. The detection effect depends on the angle of the light, ambient temperature, body size, and moving speed. The illustrated detection area is based on the direction the logo is facing.

04

**EN**

## Specifications

Model: MJYD02YL

Luminous Flux: 3 lm, 25 lm

Rated Voltage: 4.5 V

Rated Power: 0.34 W

Operating Temperature: -10°C to 40°C

Item Dimensions:  $\phi$  80 mm  $\times$  62 mm

Net Weight: Approx. 121 g

05

**EN**

## Precautions

- Do not cover the detection area of the light.
- When cleaning the surface of the light, wipe it clean with a soft cotton cloth and do not use any corrosive solvents.
- Do not install the light near heat sources such as AC or heating vents, or in direct sunlight. Nor install the light near sources of humidity such as humidifiers or water heaters.
- Make sure the Mi logo is upright at all times when installing and using the night light.
- When the brightness of the night light is reduced after a period of normal use, the battery level may be insufficient. Please replace the batteries with new ones and dispose of the used batteries in accordance with local rules and regulations, so as to avoid environmental pollution.
- The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.
- For indoor use only.

06

**EN**

- Please pay attention to the positive (+) and negative (-) poles when installing the batteries.
- After non-rechargeable batteries are depleted, they cannot be charged.
- Different types of batteries, and old and new batteries should not be mixed.
- The batteries must be removed from the night light when it is not used for a long time, or when the night light is being disposed of.
- Remove leaking batteries from the night light, and dispose of them in accordance with local rules and regulations, so as to avoid environmental pollution.

07

**EN**

## CE EU Declaration of Conformity

We Qingdao Yeelink Information Technology Co., Ltd., hereby, declare that this equipment is in compliance with the applicable Directives and European Norms, and amendments. The full text of the EU declaration of conformity is available at the following internet address:  
<http://www.mi.com/global/service/support/declaration.html>

## WEEE Disposal and Recycling

All products bearing this symbol are waste electrical and electronic equipment (WEEE as in directive 2012/19/EU) which should not be mixed with unsorted household waste. Instead, you should protect human health and the environment by handing over your waste equipment to a designated collection point for the recycling of waste electrical and electronic equipment, appointed by the government or local authorities. Correct disposal and recycling will help prevent potential negative consequences to the environment and human health. Please contact the installer or local authorities for more information about the location as well as terms and conditions of such collection points.

08